


SDM3055 Firmware Update Instruction

Note : If the firmware version is before 1.01.01.16R2 , please download the necessary update file(like the transition firmware, the CFG file and so on...) through the below website :

<https://www.siglentamerica.com/service-and-support/firmware-software/digital-multimeters/#sdm3055-series>.



Drivers
SDM3045X/SDM3055 LabVIEW Driver - 1.0 (Release Date 04.18.17) [Download](#)

SDM3055 5 ½ Digits Dual-Display Digital Multimeters

Firmware [View Release Notes](#)
SDM3055 Firmware - 1.01.01.19 (Release Date 09.01.17) [Download](#)
SDM3055 Firmware - 1.01.01.16R2 (Release Date 03.22.16) [Download](#)

Software
EasyDMM - 1.01.02.01.03 (Release Date 05.27.17) [Download](#)

Drivers
SDM3045X/SDM3055 LabVIEW Driver - 1.0 (Release Date 04.18.17) [Download](#)

[Contact Sales](#)
[Support](#)

WARNING:

Upgrading need several minutes!

Do not shut down the instrument during updating!


1. Copy the update file to the USB flash drive in the root directory.
2. Insert the USB flash drive into the USB host interface on the front panel of the multimeter.
3. Press the “Shift” softkey and the “Dual” softkey to go into Utility mode.
4. Press the “Test / Admin” softkey.




5. Press the “Firmware Update” softkey.



6. Press the “Browse” softkey.



7. Then press the right arrow key to see the files in the external drive (the USB drive).



8. Scroll down and highlight the appropriate ADS file.

9. Press the "Select" softkey. Now you will see the selected firmware file in the File Name window.

10. Press the "Update" softkey, the screen will say, Are you sure to perform it? Press "Yes".



11. When the firmware update process is finished, it will show, "Update Succeed".
12. Press the "Done" softkey, pull out the flash drive and reboot the instrument.
13. You can now check the firmware update by pressing the "Shift" softkey and the "Dual" softkey to go into the Utility mode.
14. Press the "System Setup" softkey and press the "System info" softkey and you can view the SW Version.

WARNING:

Upgrading need several minutes!

Do not shut down the instrument during updating!