

SDS2000X Firmware Update Instructions

Note: during the updating, do not cut off the power or pull out the U-disk.

1. Please firstly unzip the firmware file (.ads) in the update package to a U-disk.
2. Insert the U-disk.
3. Press **Utility** and then **Next Page** to get to the third page of the UTILITY function menu.



Figure 1 UTILITY function menu

4. Press **Update** and then choose **Firmware** to enter the file system.



Figure 2 File system

5. Use the universal knob to select the right update firmware which should be with an ADS postfix, and then press the **Press To Update** softkey, then the **Single** button to perform upgrade program. It will take about 5~6 minutes.
6. Restart the oscilloscope when comes out the prompting “Update success! Please Restart The SPO!”



Figure 3 Update successfully

Note: during the updating, do not cut off the power or pull out the U-disk.